

CEILING FIXTURE INSTALLATION INSTRUCTION MANUAL

PLEASE READ THESE INSTRUCTIONS CAREFULLY AND SAVE THEM, AS YOU MAY NEED THEM AT LATER DATE.

WARNING:

Failure to install and wire fixture in accordance with the National Electrical Codes (NEC), all applicable Federal, State and Local electrical codes, as well as specific U.L. Safety standards for the intended working environment (location/application), may cause serious personal injury, death and/or property damage. This product must be installed by a person familiar with the construction and operation of the product and the hazards involved.



TO AVOID ELECTRICAL SHOCK TURN OFF POWER AT FUSE OR BREAKER BOX.

Make sure fixture is grounded per National Electrical Codes(NEC). This fixture is suitable for damp location.

IMPORTANT NOTE:

The safe guards and instructions appearing in this page are not meant to cover all possible conditions and situations that may occur. It may be understood that common sense, cautions and care are factors which can not be built into any product. The person(s) installing, operation and responsible for the light fixture, must execute these factors.

WARNING:



Risk of fire and electrical shock, most dwellings built before 1985 have supply wires rated 60°C. Consult a qualified electrician before installing. If supply wires are located within 3 inches of the ballast, use wires rated at least 90°C. This fixture is designed for use in a 120VAC / 60Hz circuit. This fixture is compatible with a TRIAC dimming circuit.

SUGGESTED TOOLS:

Tools and material needed: screwdriver, pliers, wire nuts, electrical tape.

INSTALLATION STEPS

1. To help prevent the possibility of electrical shock, the use of rubber sole shoes is recommended.
2. Exercise care when handling the fixture to avoid cuts or abrasions.
3. If a ladder is needed, make sure to use a sturdy wooden one.
4. Screw the long mounting screws into electcal box about two complete turns. (Mounting screws included)
5. Connect the green or blue wire from the fixture to the supply power source ground wire.
For non-dimming fixture. Connect the white wire from the fixture to the white (N) wire from supply power source. Connect the black wire from the fixture to the black (L) wire from supply power source.
For TRIAC dimming. Connect the white wire from the fixture to the white (N) wire from dimming source per dimmer wiring instructions. Connect the black wire from the fixture to the black (L) wire from dimmer supply power source per dimmer wiring instructions. **Do not mix wires.** Pull on each wire lead to make sure connections are secure. Make certain no bare wires are exposed outside of wire connectors. Tuck all connections neatly into the junction box.
6. Align the canopy base over the long mounting screws so that the screw comes through the keyhole slots. Spin the canopy slightly until screws are at the small end of the keyhole slots. Tighten the self-topping screws until the canopy fits snug to the ceiling.
7. Adjust CCT switch according to the desired color temperature as shown below.



8. Align diffuser evenly on clips by placing edge of diffuser upon edge of clips. After assuring each side is evenly on the clips press down equally on the entire diffuser together to secure into place, turn the acrylic clockwise to secure into place.
9. Turn power on.

