

IMPORTANT: Read carefully before installation and retain for future reference.

- **RISK OF ELECTRICAL SHOCK.** TURN MAIN SWITCH AND CIRCUIT BREAKER TO “OFF” POSITION BEFORE SERVICE OR RELAMPING.
- All electrical connections must be in accordance with local codes, ordinances and National Electrical Code. If you are unfamiliar with proper electrical wiring or connections, secure the services of a qualified licensed electrician.
- Proper grounding of the fixture is essential for protection from shock, correct operation of the electronic driver and the elimination of electrical interference.

WARNING

- TURN OFF POWER FROM THE MAIN CIRCUIT BEFORE INSTALLING FIXTURE. Make sure fixture is grounded per National Electrical Codes (NEC).
- This product must be installed by a person familiar with the construction and operation of the product and the hazards involved.
- Risk of fire and electrical shock. Most dwellings built before 1985 have supply wires rated 140°F(60°C). Consult a qualified electrician before installing.
- If supply wires are located within 3 inches of the ballast, use wires rated at least 194°F(90°C).
- To prevent the possibility of electrical shock, the use of rubber sole shoes is recommended. Exercise care; use work gloves when handling the fixture to avoid cuts or abrasions.

PLEASE READ THESE INSTRUCTIONS CAREFULLY AND SAVE THEM, AS YOU MAY NEED THEM AT A LATER DATE.

Installation

Assembly Instructions

Step 1 – Preparing for installation.

- Disconnect electrical power at fuse or circuit breaker box before installing or servicing any part of this fixture.
- Carefully remove the fixture from the carton and check that all parts are included.
- Disassemble mounting bracket (1) from the backboard (3) by removing all necessary components per illustration shown.
- Install mounting bracket (1) to the junction box (not included).

Wiring-all wiring must take place inside junction box (not included).

Step 2 – Wiring fixture.

- Make all wire connections to appropriate wire. Secure with wire nuts (provided).
- Connect the bare or green wire from the fixture and the supply power source ground wire.
- Connect the black wire from the fixture to the black (L) wire from supply power source.
- Connect the white wire from the fixture to the white (N) wire from supply power source.
- Pull on each wire lead to make sure connections are secure. Make certain no bare wires are exposed outside of wire connectors. Tuck all connections neatly into the junction box.

Step 3 – Mounting.

- Place the backboard (3) on the mounting bracket(1), install the backboard (3) by twisting hex nuts finials(4). Make sure the unit is tightened against the wall.
- Apply a small amount of silicone (not included) per manufacturer’s instruction around the two screws(4) and around the fixture where it contacts with the surface of the wall.

Step 4 –Slide the CCT switch on the DOB of fixture to select from 3000K, 4000K, 5000K.

Step 5 – Restore power at fuse or circuit breaker box.

